

Intrusion detection system for LEACH

Software: NetSim Standard v13.3, Visual Studio 2022

Project Download Link:

https://github.com/NetSim-TETCOS/Intrusion_Detection_System_in_LEACH_v13.3/archive/refs/heads/main.zip

Follow the instructions specified in the following link to download and setup the Project in NetSim:

<https://support.tetcos.com/en/support/solutions/articles/14000128666-downloading-and-setting-up-netsim-file-exchange-projects>

Introduction

An Intrusion Detection System (IDS) is a security mechanism designed to monitor network traffic and detect unauthorized access or malicious activities. The Low-Energy Adaptive Clustering Hierarchy (LEACH) is a clustering-based protocol that divides the sensor nodes into clusters, with one node acting as the cluster head, responsible for collecting data from the cluster members this protocol is used in wireless sensor networks to reduce energy consumption and prolong network lifetime.

In the context of LEACH, an IDS can help to detect and prevent attacks that target the network's nodes, such as denial-of-service (DoS) attacks, sinkhole attacks, and compromised node attacks. IDS for the LEACH is a security solution designed specifically for WSNs that use the LEACH protocol. It works by monitoring the network traffic, analyzing it for anomalies or malicious activities, and taking appropriate actions to prevent them.

The goal of an IDS for LEACH in Netsim is to provide an additional layer of security to protect the network and the data transmitted through it. By detecting and responding to potential threats in a timely manner, the system can help prevent attacks and ensure the integrity and availability of the network.

Example

1. The **Workspace_IDS_in_LEACH** comes with a sample network configuration that are already saved. To open this example, go to Your work in the Home screen of NetSim and click on the **IDS_in_LEACH_Example** from the list of experiments.
2. This Network is created in WSN Network as per the Number of clusters and size of clusters that are set in the LEACH code. By default, the code runs for a scenario with 64 sensors uniformly placed, with the SINKNODE placed as per the screenshot shown below.




Figure 1: 64 sensors uniformly placed, with the SINKNODE

3. Wireless Link Properties

- Channel Characteristics - Pathloss only
- Path loss model - LOG_DISTANCE
- Path loss exponent – 2.5

4. Run the simulation for 100 seconds.

Results and discussion

- View the packet animation. You will note that the sensors directly start transmitting packets without route establishment since the routes are statically defined in LEACH.




Figure 2: Packet Animation Window

- You will also note that the cluster heads keep changing dynamically in Clusters 2, 3 and 4.
- In cluster1, initially the cluster members transmit packets to malicious node (device id 11) since it advertises false battery information to become a cluster head. Per the original code setting the Watchdog timer is set to 2 seconds and the failure threshold is set to 20 packets. You would notice that around 52 seconds, the malicious node is detected and then cluster head is elected dynamically based on the remaining energy of the sensor.
- This can be observed in Packet trace by applying filters to Source_ID column by selecting only Sensor-18, 20, 27 and 28 as we are checking on cluster 1 where malicious node is present and application is only configured from this particular nodes. You will be able to see that the receiver id is sensor-11 from 1s till 52s of simulation time and then it is changed when it gets blacklisted.

PACKET_ID	SEGMENT_ID	PACKET_TYPE	CONTROL_PACKET_TYPE/APP_NAME	SOURCE_ID	DESTINATION_ID	TRANSMITTER_ID	RECEIVER_ID	APP_LAYER_ARRIVAL_TIME(US)	TRX_LAYER_ARRIVAL_TIME(US)
5	1	0 Sensing	App2_SENSOR_APP	SENSOR-27	SINKNODE-65	SENSOR-27	SENSOR-19	0	0
30	2	0 Sensing	App4_SENSOR_APP	SENSOR-28	SINKNODE-65	SENSOR-28	SENSOR-11	1000000	1000000
32	2	0 Sensing	App1_SENSOR_APP	SENSOR-18	SINKNODE-65	SENSOR-18	SENSOR-11	1000000	1000000
34	2	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	1000000	1000000
40	2	0 Sensing	App4_SENSOR_APP	SENSOR-28	SINKNODE-65	SENSOR-28	SENSOR-11	1000000	1000000
62	3	0 Sensing	App4_SENSOR_APP	SENSOR-28	SINKNODE-65	SENSOR-28	SENSOR-11	2000000	2000000
64	3	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	2000000	2000000
93	4	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	3000000	3000000
95	4	0 Sensing	App4_SENSOR_APP	SENSOR-28	SINKNODE-65	SENSOR-28	SENSOR-11	3000000	3000000
101	4	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	3000000	3000000
105	4	0 Sensing	App1_SENSOR_APP	SENSOR-18	SINKNODE-65	SENSOR-18	SENSOR-11	3000000	3000000
107	4	0 Sensing	App1_SENSOR_APP	SENSOR-18	SINKNODE-65	SENSOR-18	SENSOR-11	3000000	3000000
113	5	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	4000000	4000000
117	1	0 Sensing	App2_SENSOR_APP	SENSOR-27	SINKNODE-65	SENSOR-27	SENSOR-19	0	0
119	5	0 Sensing	App2_SENSOR_APP	SENSOR-27	SINKNODE-65	SENSOR-27	SENSOR-11	4000000	4000000
121	1	0 Sensing	App2_SENSOR_APP	SENSOR-27	SINKNODE-65	SENSOR-19	SENSOR-8	0	0
128	5	0 Sensing	App1_SENSOR_APP	SENSOR-18	SINKNODE-65	SENSOR-18	SENSOR-11	4000000	4000000
131	5	0 Sensing	App1_SENSOR_APP	SENSOR-18	SINKNODE-65	SENSOR-18	SENSOR-11	4000000	4000000
142	6	0 Sensing	App4_SENSOR_APP	SENSOR-28	SINKNODE-65	SENSOR-28	SENSOR-11	5000000	5000000
144	5	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	4000000	4000000
179	7	0 Sensing	App1_SENSOR_APP	SENSOR-18	SINKNODE-65	SENSOR-18	SENSOR-11	6000000	6000000
182	5	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	4000000	4000000
183	5	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	4000000	4000000
191	7	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	6000000	6000000
212	8	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	7000000	7000000
219	8	0 Sensing	App4_SENSOR_APP	SENSOR-28	SINKNODE-65	SENSOR-28	SENSOR-11	7000000	7000000
242	9	0 Sensing	App1_SENSOR_APP	SENSOR-18	SINKNODE-65	SENSOR-18	SENSOR-11	8000000	8000000
246	8	0 Sensing	App4_SENSOR_APP	SENSOR-28	SINKNODE-65	SENSOR-28	SENSOR-11	7000000	7000000
347	6	0 Sensing	App3_SENSOR_APP	SENSOR-20	SINKNODE-65	SENSOR-20	SENSOR-11	8000000	8000000


Figure 3: NetSim Packet trace after filtering Sensor 18, 20, 27 and 28 as source ID

- Now undo filter in Source_Id column and apply filter to transmitter_Id column by selecting only Sensor-11. You will be able to see that no data packets are forwarded by the malicious node.

PACKET_ID	SEGMENT_ID	PACKET_TYPE	CONTROL_PACKET_TYPE/APP_NAME	SOURCE_ID	DESTINATION_ID	TRANSMITTER_ID	RECEIVER_ID	APP_LAYER_ARRIVAL_TIME(US)	TRX_LAYER_ARRIVAL_TIME(US)
33	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-18	SENSOR-11	SENSOR-18	N/A	N/A
35	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A
41	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-28	SENSOR-11	SENSOR-28	N/A	N/A
63	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-28	SENSOR-11	SENSOR-28	N/A	N/A
65	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A
96	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-28	SENSOR-11	SENSOR-28	N/A	N/A
102	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A
108	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-18	SENSOR-11	SENSOR-18	N/A	N/A
120	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-27	SENSOR-11	SENSOR-27	N/A	N/A
132	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-18	SENSOR-11	SENSOR-18	N/A	N/A
143	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-28	SENSOR-11	SENSOR-28	N/A	N/A
180	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-18	SENSOR-11	SENSOR-18	N/A	N/A
192	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A
250	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A
254	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-27	SENSOR-11	SENSOR-27	N/A	N/A
258	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A
266	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-27	SENSOR-11	SENSOR-27	N/A	N/A
274	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-27	SENSOR-11	SENSOR-27	N/A	N/A
276	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A
285	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-27	SENSOR-11	SENSOR-27	N/A	N/A
287	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A
299	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-27	SENSOR-11	SENSOR-27	N/A	N/A
306	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-18	SENSOR-11	SENSOR-18	N/A	N/A
310	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A
312	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-18	SENSOR-11	SENSOR-18	N/A	N/A
320	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-27	SENSOR-11	SENSOR-27	N/A	N/A
331	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A
352	0 N/A	Control_Packet	Zigbee_ACK	SENSOR-11	SENSOR-20	SENSOR-11	SENSOR-20	N/A	N/A

Figure 4: Undo filter in Source_Id column and transmitter_Id column by selecting only Sensor-11


- This will have a direct impact on the Application Throughput which can be observed in the Application Metrics table present in NetSim Simulation Results window. The throughput for applications 1, 2, 3 and 4 are less since the source ids belongs to cluster1 having malicious node (device id 11).



Application ID	Application Name	Packets Generated	Packets Received	Throughput (Mbps)	Delay (microsecond)	Jitter (microsecond)
1	App1_SENSOR_APP	100	14	0.000056	1342797.800000	2770871.507692
2	App2_SENSOR_APP	100	17	0.000068	1423719.952941	1818326.687500
3	App3_SENSOR_APP	100	19	0.000076	2008382.547368	2894091.811111
4	App4_SENSOR_APP	100	18	0.000072	1284034.855556	1539476.552941
5	App5_SENSOR_APP	100	43	0.000172	895294.023256	1772288.261905
6	App6_SENSOR_APP	100	36	0.000144	391253.661111	382317.588571
7	App7_SENSOR_APP	100	40	0.000160	913838.985000	1442038.010256
8	App8_SENSOR_APP	100	36	0.000144	629259.627778	1207585.571429
9	App9_SENSOR_APP	100	60	0.000240	286170.370000	483057.155932
10	App10_SENSOR_APP	100	39	0.000156	284984.205128	429237.405263

Figure 6: Application Metrics Window

- The time at which a malicious node is detected can be obtained from the CUSTOM METRICS in the results window where the start time - time from which a node becomes malicious, detection time - time at which the node was added to blacklist can be obtained.



DeviceID	Start Time (micro sec)	Detection Time (micro sec)
11	0.000000	52016278.400000

Figure 7: Dedicated Metrics for IDS

Files Used in this project

The following steps show how a user can run the IDS in NetSim to detect a malicious node, and then setup a new route to the destination avoiding the malicious node.

- Creating Malicious nodes for a particular network scenario is explained in Malicious.c file which is present in DSR Project.
- Clustering and cluster head election is explained in LEACH.c file which is present in DSR Project.

For this implementation of LEACH, the number of Clusters is fixed as 4 and all the 4 clusters are equal. If the user wants to change it, then he/she must also change the static routing for the Cluster Heads and the ClusterElement array accordingly in **leach.c**




Figure 8: Sensor nodes present in each Clusters

To make 4 equal clusters the number of sensors must be 4,16,36,64,100. Depending on the number of sensors, the ClusterElements array must be defined. Here, it has been defined and commented for 4,16,36,64,100 sensors. Uncomment the one you want to use.

```

File Edit View Git Project Build Debug Test Analyze Tools Extensions Window Help Search (Ctrl+Q) NetSim
DSR
leach.c
25 //*****
26
27
28 #include "main.h"
29 #include "DSR.h"
30 #include "List.h"
31 #include "../BatteryModel/BatteryModel.h"
32 #include "../ZigBee/802_15_4.h"
33 #include "Pathtracer.h"
34 #define NUMBEROFCLUSTERS 4
35 #define SIZEOFCLUSTERS 16 //SIZEOFCLUSTERS can be 1,4,9,16,25
36
37 static int CHcount[NUMBEROFCLUSTERS];
38 static int prevCH[NUMBEROFCLUSTERS];
39
40
41
42 //For 100 sensors and SIZEOFCLUSTERS = 25, uncomment this
43 //int ClusterElements[NUMBEROFCLUSTERS][SIZEOFCLUSTERS] = {{1,2,3,4,5,11,12,13,14,15,21,22,23,24,25,31,32,33,34,35,41,42,43,44,45},\
44 {6,7,8,9,10,16,17,18,19,20,26,27,28,29,30,36,37,38,39,40,46,47,48,49,50},\
45 {51,52,53,54,55,61,62,63,64,65,71,72,73,74,75,81,82,83,84,85,91,92,93,94,95},\
46 {56,57,58,59,60,66,67,68,69,70,76,77,78,79,80,86,87,88,89,90,96,97,98,99,100}};
47
48 //For 64 sensors and SIZEOFCLUSTERS = 16, uncomment this
49 int ClusterElements[NUMBEROFCLUSTERS][SIZEOFCLUSTERS] = {{1,2,3,4,9,10,11,12,17,18,19,20,25,26,27,28},\
50 {5,6,7,8,13,14,15,16,21,22,23,24,29,30,31,32},\
51 {33,34,35,36,41,42,43,44,49,50,51,52,57,58,59,60},\
52 {37,38,39,40,45,46,47,48,53,54,55,56,61,62,63,64}};
53
54 //For 36 sensors and SIZEOFCLUSTERS = 9, uncomment this
55 //int ClusterElements[NUMBEROFCLUSTERS][SIZEOFCLUSTERS] = {{1,2,3,7,8,9,13,14,15},{4,5,6,10,11,12,16,17,18},{19,20,21,25,26,27,31,32,33},{22,23,24,28,29,30,34,35,36}};
56
57 //For 16 sensors and SIZEOFCLUSTERS = 4, uncomment this
58 //int ClusterElements[NUMBEROFCLUSTERS][SIZEOFCLUSTERS] = {{1,2,5,6},{3,4,7,8},{9,10,13,14},{11,12,15,16}};
59
60 //For 4 sensors and SIZEOFCLUSTERS = 1, uncomment this
61 //int ClusterElements[NUMBEROFCLUSTERS][SIZEOFCLUSTERS] = {{1},{2},{3},{4}};
62

```

Figure 8: Leach.c file present in DSR project

- To detect the intruder and to send data via a new route, the following files are added in DSR(Pathrater.c) and Zigbee(Watchdog.c)

Pathrater.c :

This file contains code for avoiding the malicious node and finding a new route (once the IDS detects the malicious node) in networks running DSR in Layer 3. Note that this system would work only for UDP and not for TCP, since TCP involves receiving ack's from the destination.

If `_NETSIM_PATHRATER_` is defined, the code is used to validate routes. When the Node is a Malicious Node and a Route Reply is processed, the Function verifies the route reply in the route cache and checks for the blacklisted node.

i.e.,malicious node. When a malicious node is found that route entry is deleted from the cache.

Watchdog.c

This file contains code for the IDS and is added in Zigbee operating in Layer 3.

If `_NETSIM_WATCHDOG_` is defined, a watchdog timer starts the moment a packet is sent. Once a packet is forwarded to next hop node, the current node checks for watchdog timer duration if the packet is getting forwarded further on to destination node or not.

The malicious node does not forward packets that it receives. The watchdog timer in the node (which forwarded the packet to the malicious node) expires. A counter is present which measures the number of times the watchdog timer expires (in other words the number of packets sent out but not forwarded by the next hop node). Once this counter's value reaches the failure threshold the next hope is marked by the current node as a malicious node.